

# Installation Instructions

## NLOS

### Surf LED Regressed Edge-Lit Surface Mount

**READ PRIOR TO ATTEMPTING INSTALLATION**  
**ALWAYS TURN OFF MAIN POWER BEFORE INSTALLATION**  
**INSTALLATION SHOULD BE CARRIED OUT BY YOUR LOCAL ELECTRICIAN**

**⚠ IMPORTANT** - This equipment is intended to be installed only by qualified personnel. The installation must be made in accordance with the current edition of the National Electrical Code and all applicable state and local building codes. The final installation must be approved by the appropriate, qualified electrical/building inspector(s). Improper installation may result in a fire or electrical hazard. Be sure the electrical power to the circuit has been disconnected before installing this electrical system.

**⚠ IMPORTANT** - Cet équipement est destiné à être installé uniquement par du personnel qualifié. L'installation doit être faite conformément à l'édition actuelle du Code national de l'électricité et à tous les codes de construction locaux et nationaux applicables. L'installation finale doit être approuvée par un ou plusieurs inspecteurs qualifiés en électricité / bâtiment. Une installation incorrecte peut entraîner un incendie ou un risque électrique. Assurez-vous que l'alimentation électrique du circuit a été déconnectée avant d'installer ce système électrique.

#### INSTALLATION INSTRUCTIONS

1. Fully remove mounting screws from 4" octagonal junction box. (Figure 1) **NOTE:** Make sure 4" octagonal junction box has minimum 1-1/2" height
2. Align and secure junction box mounting plate to junction box using mounting screws. (Ground junction box mounting lead must face room side) Make sure junction box mounting plate is firmly against the ceiling. Do not overtighten mounting screws, this could distort the plate.
3. Pull supply wires from junction box through hole in junction box mounting plate.
4. While supporting the luminaire body, make electrical connections: black lead to hot (Black) supply lead; white lead to neutral (White) supply lead. Un-insulated wires are ground wires (ground junction box mounting lead and ground luminaire lead) must be connected to grounding terminal or ground (Green) supply lead inside junction box. Use WIRE NUTS to make connections (Figure 2)
5. Carefully push connections back into junction box.
6. Align two springs and driver or luminaire body to the opening in the junction box mounting plate. Snap luminaire body into plate. (Figure 3)

**⚠ CAUTION:** Make certain that no wires are pinched between junction box mounting plate and luminaire body. To remove luminaire body from the ceiling, pull straight down.

**DRIVER REPLACEMENT:** Inseparable luminaire. Do not attempt to service. Replace entire fixture.

