

LED EXIT & EMERGENCY

LED Exit & LED Emergency Combination

Dual 120V/277V input

Nora's all LED Exit sign with dual emergency fixtures feature Ball and Socket LED Lights for full adjustability. Exit sign is powered by LED source for maximum life without maintenance; Expected Life 100,000 hours. In the event of power loss, both sign and heads will operate for a minimum of 90 minutes.

FEATURES

- Fully adjustable 2.8 watt high-intensity LED heads
- Universal Mounting - Wall or ceiling
- UL Listed and meets or exceeds UL924, NEC, OSHA and NFPA 101 Life Safety Code requirements
- Injection molded high impact and scratch resistant corrosion-proof and UL94 5V-0 flame retardant housing
- Push-To-Test Switch
- Maintenance free NiCad battery
- 120V or 277V AC input
- Field selectable Chevrons
- 6" High and 3/4" Stroke letters
- External LED Status indicator
- Available in Black or White
- 100,000 hour expected life
- Damp Location Listed
- Wet Location shield accessory available



committed to
GREEN



NEG-730



NEG-730 + NEX-730-LED/R

LED EXIT & LED EMERGENCY COMBINATION

CATALOG. NO.	DESCRIPTION	WATTAGE	BODY	EXIT LETTERS
NEX-730-LED	LED Exit & Emergency Combo	2.8	Black, White	Green, Red
NEG-730	Weather Proof Cover		White	

Finishes: **B** - Black, **(Blank)** - White

LED Exit Letters: **G** = Green, **R** = Red

Example: **NEX-730-LED/RB** - LED Exit & LED Emergency Combo, Red Exit Letters, Black housing

Illuminating the future...since 1989

TEL. 800.686.6672 | FAX 800.500.9955 | WWW.NORALIGHTING.COM