

NTH-115

Universal Lamp Holder

Source: 150W R/PAR/BR max.

Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT DESCRIPTION

Lamp holder suitable for applications requiring higher wattage lamp sources. Construction is minimal with a short adjustment bracket connecting high heat rated socket with contact head.

FEATURES

- White glazed porcelain bare socket
- Heat resistant teflon coated wire lead
- Low profile mounting / adjustment arm
- High strength stainless steel electrical contacts
- One or two circuit track capable
- Accepts LED lamps

CONSTRUCTION

Adjustment Arm: 0.080" Rigid steel "L-bracket" connects fixture housing to electrical contact head. Screw locks angle position to prevent loss of angle from constant heat exposure.

ELECTRICAL SYSTEM

Voltage: 120V input

Socket: Medium base

Lamp: R/PAR20, BR/PAR30 or BR40/PAR38 (not included)

Wattage: 150W max.

ONE/TWO CIRCUIT CONVERSION

Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

LABELS AND LISTINGS

UL Listed




PRODUCT IMAGES AND DIMENSIONS



shown with
PAR20

shown with
PAR30

shown with
PAR38



Universal Lamp Holder

Catalog No.	Finish	Adapter
NTH-115	W = White	(blank) = H-style
		/J = J-style
		/L = L-style

Example: NTH-115W = Universal Lamp Holder, White finish, H-Style Adapter