

NTH-123

Wireback Cone Track Head

Lamp: 50W R20/PAR20 max.

Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT DESCRIPTION

Streamlined wireback mesh conical R20/PAR20 track lighting fixture with internal friction position hold.

FEATURES

- Sleek, modern conical design
- Wire mesh decorative design feature
- High-strength stainless steel electrical contacts
- One or two circuit track capable
- Accepts LED lamps

CONSTRUCTION

Housing: Main body consists of 0.025" wire screen cone terminating at a 0.025" finishing trim. Small end of cone allows for screw attachment to rear body of fixture. Socket cup is a two-piece 0.10" injection molded high-heat rated assembly. Black rubber "O" ring provides additional design feature and protects mesh and socket cup from scratches or other damage.

Structural Arm: Extruded 0.055" aluminum arm connects fixture housing to electrical contact head. Internal tightening mechanism maintains desired lamp aiming angles. Structural arm also functions as wire way, completely concealing lead wire from socket to contact head.

ELECTRICAL

Voltage: 120V input

Socket: Medium base

Lamp: 50W R20/PAR30 max. (not included)

ONE/TWO CIRCUIT CONVERSION


Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

LABELS AND LISTINGS

UL Listed



PRODUCT IMAGES AND DIMENSIONS



Wireback Cone Track Head

Catalog No.	Finishes	Style
NTH-123	W = White	(blank) = H-style
		/J = J-style
		/L = L-style

Example: NTH-123W = Wireback Cone Track Head, White Finish, H-Style Adapter