

NTL-213

MR16 Low Voltage Wireback Track Head

Lamp: 20W - 75W Halogen MR16

Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT DESCRIPTION

Low voltage die cast aluminum designer cylinder fixtures with MR16 light source. Yoke provides full adjustment of light source for special aiming and dual tightening knobs assure secure lock on angle position.

FEATURES

- Die cast aluminum provides superior strength and rigidity
- Low profile, aesthetic design
- Adjustable stem for custom aiming
- Clear shield included with fixture
- High-strength stainless steel electrical contacts
- One or two circuit track capable

CONSTRUCTION

Contact Head Assembly: Three .030 stainless steel contacts mounted in high heat rated plastic housing.

Housing: Main body consists of 0.025 wire screen cone terminating at a 0.025 finishing trim. Small end of cone allows for screw attachment to rear body of fixture. Rear portion of fixture is constructed of 0.090 die-cast aluminum with vented rear providing design feature and heat dissipation and escape.

Stem: 0.065 Die-cast aluminum stem connects fixture housing to electrical contact head. Lead wire is completely concealed from view within stem. Dual plastic angle tightening knobs maintain clean, decorative appearance of the fixture and provide secure angle position.

ELECTRICAL

Input Voltage: 120V 60Hz

Output Voltage: 12V 6.25A

Socket: GU5.3 porcelain socket

Transformer: Solid state electronic transformer provides noise-free voltage reduction and operation.

Lamp: 20W - 50W 12V Halogen MR16 (not included). **Note:** Do not use provided glass lens when MR16 lamp already comes with lens.

Dimming: ELV

ONE/TWO CIRCUIT CONVERSION


Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

LABELS AND LISTINGS

UL Listed



PRODUCT IMAGES AND DIMENSIONS



MR16 Low Voltage Wireback Track Head

Finish

NTL-213NB = Natural Metal Body / Black Adapter

Example: **NTL-213NB** = MR16 Low Voltage Wireback Track Head, Natural Metal Body / Black Adapter