

Installation Instructions

NTE-8803

Dipper Track Head

READ PRIOR TO ATTEMPTING INSTALLATION
ALWAYS TURN OFF MAIN POWER BEFORE INSTALLATION
INSTALLATION SHOULD BE CARRIED OUT BY YOUR LOCAL ELECTRICIAN

ITEM #	DESCRIPTION	COLOR TEMP.
NTE-88031530 NTE-88031535 NTE-88031540	Dipper Track Head 15W	3000K 3500K 4000K
NTE-88033030 NTE-88033035 NTE-88033040	Dipper Track Head 30W	3000K 3500K 4000K

- ⚠ WARNING** - Risk of fire or electric shock. LED fixture installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician.
- ⚠ WARNING** - Risk of fire or electric shock. Install this fixture only in luminaires that have the construction features and dimensions shown in the photographs and / or drawings and where the input rating does not exceed the input rating of the luminaire.
- ⚠ WARNING** - To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- ⚠ WARNING** - This equipment is intended to be installed only by qualified personnel. The installation must be made in accordance with the current edition to the National Electric Code and all applicable state and local building codes. The final installation must be approved by the appropriate qualified electrical/building inspector(s). Improper installation may result in a fire or electrical hazard. Be sure the electrical power to the circuit has been disconnected before installing this electrical system.
- ⚠ AVERTISSEMENT** - Cet équipement est destiné à être installé uniquement par du personnel qualifié. L'installation doit être faite en conformité avec l'édition actuelle du Code national de l'électricité et toutes étatiques et locales codes du bâtiment applicables. L'installation finale doit être approuvée par l'inspecteur en électricité / bâtiment qualifié approprié(s). Une mauvaise installation peut entraîner un incendie ou un risque électrique. Soyez sûr de la puissance électrique vers le circuit a été coupée avant l'installation de ce système électrique.

INSTRUCTIONS:

NOTE: LED track head comes ready to install right out of the box.

1. Turn off power before beginning installation.
2. Use cog and slider to put the contact head adapter to unlock position and insert into the track. (Figure 1)
3. Make sure the polarity lines on both track and fixture are aligned.
4. Push the fixture straight into track, and put contact head adapter to lock position. (Figure 2)
5. To aim, rotate fixture horizontally from adapter and vertically from head.

REMOVAL INSTRUCTIONS:

1. To remove, set contact head adapter to unlock position and remove from track.

