

Dimmer Compatibility

NHAPIC-3

120V input: Phase Dimming (P)				
	1000lm / 10W (L1)		1500lm / 15W (L2) & 2000lm / 20W (L3)	
Manufacturer	Brand	Model #	Brand	Model #
Lutron	Diva LED+	DVCL-153P	Diva LED+	DVCL-153P
	Lumea LED+	LGCL-153P	Diva	DVELV-303P
	Skylark LED+	SCL-153P	Maestro	MAELV-600
	Toggler LED+	TGCL-153P	Maestro LED+	MACL-153M
			Skylark LED+	SCL-153P
			Skylark	SELV-300P
			Toggler LED+	TGCL-153P
Eaton	Accell	AAL06A		

CONSULT THE DIMMER MANUFACTURER PRIOR TO INSTALLATION TO ENSURE COMPATIBILITY

Dimmer Compatibility

NHAPIC-3

120-277V input: 0-10V 1% Dimming (C)		
	1000lm / 10W (L1), 1500lm / 15W (L2) & 2000lm / 20W (L3)	
Manufacturer	Brand	Model #
Leviton	IllumaTech	IP710-LFZ
Lutron	0-10V control interface	GRX-TVI
	Diva	DVSTV DVSTV-453
	Maestro	MS-Z101
	Nova	NTSTV
	Visit www.lutron.com/advance for an updated list of compatible dimmers	
Philips	Sunrise	SR1200ZTUNV

120-277V input: 0-10V 0.1% Dimming (C01)		
	1000lm / 10W (L1), 1500lm / 15W (L2) & 2000lm / 20W (L3)	
Manufacturer	Brand	Model #
Encelium	LCM	EN-ILCM-1R10V-GB2-BK EN-LCM-1R10V-GB2BKDR
	ALC	EN-ALC-1R10V-GB2-BK EN-ALC-1R10V-GB2BKDR
Legrand	WattStopper	ADF-120277
Leviton	IllumaTech	IP710-DLZ
Lutron	Diva	DVTV
Synergy Lighting Controls	ISD BC	ISD BC 120/277

CONSULT THE DIMMER MANUFACTURER PRIOR TO INSTALLATION TO ENSURE COMPATIBILITY

Dimmer Compatibility

NHAPIC-3

120/277V input: Lutron EcoSystem (L01)					
1000lm / 10W (L1), 1500lm / 15W (L2) & 2000lm / 20W (L3)					
Lutron EcoSystem Compatible Controls	Model #		Drivers per Control		
	120V	277V	EcoSystem Loops per Control	Drivers per EcoSystem Loop	Maximum Drivers per Control
PowPak Dimming Modules	RMJ-EC032-DV-B		1	32	32
	FCJ/FCJS-ECO		1	3	3
Energi Savr Node	QSN-1ECO-S		1	64	64
	QSN-2ECO-S		2	64	128
GRAFIK Eye QS HomeWorks QS Control Unit	QSGRJ-_E (wireless)		1	64	64
	QSGR-_E				
Quantum Hub	QP2-_ _2C		2	64	128
	QP2-_ _4C		4	64	256
	QP2-_ _6C		6	64	384
	QP2-_ _8C		8	64	512

CONSULT THE DIMMER MANUFACTURER PRIOR TO INSTALLATION TO ENSURE COMPATIBILITY